



## SPECIFICATION

- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- PHANTOM, PFL switch on all input
- Built in 99 program digital effect
- USB interface for MP3 input and playback with digital display
- BLUETOOTH function
- 7 band graphic EQ
- +48V phantom power supply

### SPECIFICATION :

Power Output .....	200W x 2 @ 8Ω
.....	350W x 2 @ 4Ω
Frequency Response .....	10Hz - 60KHz
Distortion (THD & N) .....	0.01%
Signal to Noise Ratio .....	112dB
Equalization : High .....	+/-15dB, 12kHz
: Mid .....	+/-15dB, 2.5kHz
: Low .....	+/-15dB, 80Hz

### PFX-6

6 Mono input power mixer

### PFX-8

8 Mono input power mixer

Mic Input .....	Electronically balanced
Gain Range .....	+6dB to +60dB
Line Input .....	Electronically balanced
Line Level Range .....	+10dBu to -40dBu
Max Output .....	+22dBu balanced
Aux Send Max Out .....	+22dBu unbalanced
Control Room Out .....	+22dBu unbalanced