


With MP3 function.
Music five band equalizer, MIC two band equalizer.
Adopts professional amplifier technology design,
strong output, low distortion, good sound quality.



Q SERIES KARAOKE AMPLIFIER

▶ Q8000 ▶ Q10000 ▶ Q20000



Technical parameters and specifications

| Model | Q8000 | Q10000 | Q20000 |
|----------------------------|-------------------------|----------|----------|
| THD Distortion | <0.03% @ 8 Ω 1KHz 1/3Po | | |
| SNR | >95db | | |
| Input Sensitivity(MIC) | 6mv | | |
| Input Sensitivity(MUSIC) | 250MV | | |
| Frequency response (MIC) | 40HZ-15KHz | | |
| Frequency response (MUSIC) | 20HZ-25KHz +/-0.5dB@1W | | |
| Output power | 200W × 2 | 250W × 2 | 450W × 2 |
| Power | 220-240V | | |
| Dimension (L × H × W) | 482x66x400 | | |



สกท.1195-2536
บริษัท โปรยูโร เทค จำกัด

